

CS Basics

1) Bases 2, 4, 8, 16, etc.

E. Benoist & C. Grothoff
Fall Term 2018-19

Bases

- Martian base
- Octal
- Hexadecimal
 - Conversions
 - Arithmetic in hexadecimal
- Binary
 - Hex as shorthand for binary

Martian base

- ▶ **Signs used for counting**
 - ▶ 1, 2, 3, 4, 5, 6, 7, 8, 9, and 0
 - ▶ a number is a list of signs 123 means $1 \times 100 + 2 \times 10 + 3$.
- ▶ **Other bases were used over the time**
 - ▶ Base 12 (for hours for instance)
 - ▶ Base 60 (for minutes for instance) 50 minutes and 33 seconds is a time counted in bases 60, It makes $50 \times 60 + 33 = 3033$ seconds
btw: $60 = 5 \times 12$
- ▶ **In the 70's other bases were used to teach counting**
 - ▶ "Modern mathematics"

How do Martians count?¹

▶ We have seen numbers on the planet Mars

▶ $\equiv f n \equiv \Theta$ or $n n f \Theta$

▶ We have found the way the Martians count:

Θ	theta	0
f	int	1
n	cap	2
\equiv	equiv	3
$f \Theta$	int, theta	4
$f f$	int, int	5
$f n$	int, cap	6
$f \equiv$	int, equiv	7
$n \Theta$	cap, theta	8
$n f$	cap, int	9
$n n$	cap, cap	10
$n \equiv$	cap, equiv	11
$\equiv \Theta$	equiv, theta	12
$\equiv f$	equiv, int	13
$\equiv n$	equiv, cap	14
$\equiv \equiv$	equiv, equiv	15
$f \Theta \Theta$	int, theta, theta	16

Use Martian base

▶ **Meaning of $n n f \Theta$**

- ▶ Θ (theta) in the first column = 0
- ▶ f (int) in the second column = $f \times f \Theta = 1 \times 4 = 4$
- ▶ n (cap) in the third column = $n \times f \Theta \Theta = 2 \times 4^2 = 32$
- ▶ n (cap) in the fourth column = $n \times f \Theta \Theta \Theta = 2 \times 4^3 = 2 \times 64 = 128$
- ▶ $n n f \Theta = \Theta + f \times f \Theta + n \times f \Theta \Theta + n \times f \Theta \Theta \Theta = 0 + 4 + 32 + 128 = 164$

Counting in Martian

▶ **Each symbol has a value**

- ▶ Θ theta, 0
- ▶ f , int, 1
- ▶ n , cap, 2
- ▶ \equiv , equiv, 3

▶ Symbol *int* (int) is the unit

▶ Symbol Θ (theta) is just a place holder

▶ **The value of a number depends on where a symbol is placed**

- ▶ First column on the right: value of the symbol
- ▶ Second column on the right: value of the symbol $\times f \Theta$ (i.e. 4)
- ▶ Third column : value of the symbol $\times f \Theta \Theta$ (i.e. $16 = 4^2$)

Use Martian base

▶ **Meaning of $\equiv f \equiv n \Theta$**

- ▶ Θ (theta) in the first column = 0
- ▶ n (cap) in the second column = $n \times f \Theta = 2 \times 4 = 8$
- ▶ \equiv (equiv) in the third column = $\equiv \times f \Theta \Theta = 3 \times 4^2 = 3 \times 16 = 48$
- ▶ *int* (int) in the fourth column = $f \times f \Theta \Theta \Theta = 1 \times 4^3 = 1 \times 64 = 64$
- ▶ *equiv* (equiv) in the fifth column = $\equiv \times f \Theta \Theta \Theta \Theta = 3 \times 4^4 = 3 \times 256 = 768$
- ▶ $n n f \Theta = \Theta + f \times f \Theta + n \times f \Theta \Theta + n \times f \Theta \Theta \Theta = 0 + 8 + 48 + 64 + 768 = 888$

Essence of a number base

- ▶ **Romans used a system where letters represented values**
 - ▶ MMXIV means 2014
 - ▶ MCMXC means 1990
 - ▶ The positions of the letters are not bounded to a column, but rather to their neighbors (for adding or subtracting)
- ▶ **We use only columnar systems: the position of a number means the value**
 - ▶ in all bases 10 (or $\int \Theta$ for martians) represents the base
 - ▶ Number in column number 0 is multiplied by $base^0 = 1$
 - ▶ Number in column number 1 is multiplied by $base^1 = 10_{base}$
 - ▶ Number in column number 2 is multiplied by $base^2 = 100_{base}$
 - ▶ Number in column number 3 is multiplied by $base^3 = 1000_{base}$



Octal

- ▶ **Counting in octal**
 - ▶ 0, 1, 2, 3, 4, 5, 6, 7, 10
 - ▶ We do not use 8 and 9 anymore
 - ▶ 10 means 8
 - ▶ 11 means 9
 - ▶ 12 means 10
- ▶ **Octal uses base 8**
 - ▶ So the 8 does not exist!
 - ▶ 27 octal means $7 + 2 \times 8$

Octal table

0	zero	0
1	one	1
2	two	2
3	three	3
4	four	4
5	five	5
6	six	6
7	seven	7
10	ten octal	8
11	eleven octal	9
12	twelve octal	10
13	thirteen octal	11
14	fourteen oct.	12
15	fifteen oct.	13
16	sixteen oct.	14
17	seventeen oct.	15
20	twenty oct.	16

The octal numbers

- ▶ **Value of a number depends on its column**
 - ▶ A number in the unit column (column number 0) is just its value
 - ▶ 7 octal means 7
- ▶ **Column number one is multiplied by 8**
 - ▶ 10 octal means 8
 - ▶ 20 octal means 16
 - ▶ 70 octal means $7 \times 8 = 56$
- ▶ **Column number two is multiplied by 64**
 - ▶ 100 octal means 64

The powers of 8

- ▶ $1_{octal} = 8^0 = 1$
- ▶ $10_8 = 8^1 = 8$
- ▶ $100_8 = 8^2 = 64$
- ▶ $1\ 000_8 = 8^3 = 512$
- ▶ $1\ 0000_8 = 8^4 = 4096$
- ▶ $100\ 000_8 = 8^5 = 32\ 768$

Converting from octal into decimal

- ▶ **Suppose we have the number 76225_8**
 - ▶ $76225_8 = 70000_8 + 6000_8 + 200_8 + 20_8 + 5_8$
 - ▶ $5_8 = 5 \times 1 = 5$
 - ▶ $20_8 = 2 \times 10_8 = 2 \times 8^1 = 16$
 - ▶ $200_8 = 2 \times 100_8 = 2 \times 8^2 = 128$
 - ▶ $6000_8 = 6 \times 1000_8 = 6 \times 8^3 = 3072$
 - ▶ $70000_8 = 7 \times 10000_8 = 7 \times 8^4 = 28672$

Hexadecimal

Hexadecimal

▶ Hexadecimal = base 16

- ▶ Is the real base for programmers

▶ Digits

- ▶ 0, 1, 2, 3, 4, 5, 6, 7, 8, 9,
- ▶ A (10), B (11), C (12), D (13), E (14), F (15)
- ▶ 16 is the base and therefore written 10 in Hexadecimal

▶ Counting

- ▶ 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 1A, 1B, 1C, 1D, 1E, 1F, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 2A, 2B, 2C, 2D, 2E, 2F, 30

▶ Notation

- ▶ In the remainder of this course, we will denote Hexadecimal numbers with a finishing H.
- ▶ So 1 becomes 1H or 2F becomes 2FH

Hexadecimal table I

0H	zero	0
1H	one	1
2H	two	2
3H	three	3
4H	four	4
5H	five	5
6H	six	6
7H	seven	7
8H	eight	8
9H	nine	9
AH	A	10
BH	B	11
CH	C	12
DH	D	13
EH	E	14
FH	F	15
10H	One -oh hexadecimal	16
11H	One -one hexadecimal	17
12H	One -two hex.	18
13H	One -three hex.	19
14H	One -four hex.	20

Hexadecimal table II

15H	One -five hex.	21
16H	One -six hex.	22
17H	One -seven hex.	23
18H	One -eight hex.	24
19H	One -nine hex.	25
1AH	One -A hex.	26
1BH	One -B hex.	27
1CH	One -C hex.	28
1DH	One -D hex.	29
1EH	One -E hex.	30
1FH	One -F hex.	31
20H	Two -oh hex.	32

Table of powers of 16

▶ Hexadecimal uses powers of 16

1H	16 ⁰	1
10H	16 ¹	16
100H	16 ²	256
1000H	16 ³	4096
10000H	16 ⁴	65536
100000H	16 ⁵	1048576
1000000H	16 ⁶	16777216

Anatomy of a number

- ▶ Let us evaluate the number $3C0A9H$

$$\begin{array}{r} 9H \\ A 0H \\ 0 0H \\ C 0H \\ + 3 0H \\ \hline 3 0 9H \end{array}$$

- ▶ $3 \times 65536 + 12 \times 4096 + 0 \times 256 + 10 \times 16 + 9 \times 1$
- ▶ $196608 + 49152 + 0 + 160 + 9 = 245929$

Conversions

From Hex to Decimal

- ▶ **Method**
 - ▶ Compute the value of each column and add the results
- ▶ **Decimal value of $7A2H$**
 - ▶ add 2 (for the 2 in column 0)
 - ▶ add 10×16 (for the A in column 1)
 - ▶ add 7×256 (for the 7 in column 2)

Other example

- ▶ **Value of $C6F0DBH$**
 - ▶ $B \times 1 = 11$
 - ▶ $D \times 16 = 13 \times 16 = 208$
 - ▶ $0 \times 256 = 0$
 - ▶ $F \times 4096 = 15 \times 4096 = 61\,440$
 - ▶ $6 \times 65\,536 = 393\,216$
 - ▶ $C \times 1\,048\,576 = 12 \times 1\,048\,576 = 12\,582\,912$
- ▶ **Total = 13 037 787**

From Decimal to Hex

- ▶ **We want to write 449 in hex.**
 - ▶ Find the largest hex column value that is contained at least once in 449
4096 is too large, and 256 is perfect.
 - ▶ find which number of 256 goes into 449 (remember 5th Grade division)
 - ▶ $449/256 = 1.7539$ so 1 is the leftmost hex digit
 - ▶ Let us subtract 1×256 from 449, we obtain 193
 - ▶ The next power of 16 is 16 itself, how many times 16 goes into 193
 - ▶ $193/16 = 12.0625$, so *C* is the next hex digit
 - ▶ $193 - 12 * 16 = 1$ the remainder is one and the next value of 16 (i.e. 16^0) is 1, so the next hex digit is 1
- ▶ **The hex value of 449 is 1C1H**

Another example

- ▶ **What is the hex value of 988 664**
 - ▶ The largest power of 16 contained in the number is 65 536
 - ▶ 65 536 goes 15 times in 988 664, so the left most hex digit is **F**.
 - ▶ The remainder is $988\ 664 - 65\ 536 \times 15 = 5624$
 - ▶ The next power of 16 is 4096, which goes only once in 5624. So the next hex digit is **1**.
 - ▶ The remainder is $5624 - 4096 = 1528$
 - ▶ The next power of 16 is 256, 256 goes 5 times into 1528
 - ▶ The next hex digit is **5**
 - ▶ The remainder is $1528 - 5 * 256 = 248$
 - ▶ The next of 16 is 16 itself, 16 goes 15 times into 148
 - ▶ The next hex digit is **F**
 - ▶ The remainder is $148 - 16 \times 15 = 8$
 - ▶ The last hex digit is **8**
- ▶ **The hex value is F15F8H**

Arithmetic in hexadecimal

Arithmetic in Hex

- ▶ **You need to do arithmetic directly in Hex**
 - ▶ Conversion to decimal and back from it will be impossible
 - ▶ for instance to add *CH* and *FH*,
 - ▶ *CH* is 12, *FH* is 15, $CH + FH$ is 27
 - ▶ then we convert 27 back into hex: *1BH*
- ▶ **Need to learn additions by heart**
 - ▶ Use flash cards for instance

Additions in Hex V

$$\begin{array}{r} F \\ +B \\ \hline 1AH \end{array} \quad \begin{array}{r} E \\ +C \\ \hline 1AH \end{array} \quad \begin{array}{r} D \\ +D \\ \hline 1AH \end{array}$$

$$\begin{array}{r} F \\ +C \\ \hline 1BH \end{array} \quad \begin{array}{r} E \\ +D \\ \hline 1BH \end{array}$$

$$\begin{array}{r} F \\ +D \\ \hline 1CH \end{array} \quad \begin{array}{r} E \\ +E \\ \hline 1CH \end{array}$$

$$\begin{array}{r} F \\ +E \\ \hline 1DH \end{array} \quad \begin{array}{r} F \\ +F \\ \hline 1EH \end{array}$$

Columns and carries

- ▶ **Method for adding hex numbers**
- ▶ **Add each column starting from the right and carry into the next column anytime the result exceeds 0FH**

$$\begin{array}{r} 1 \qquad \qquad 1 \\ 2 \ F \ 3 \ 1 \ A \ DH \\ + \ 9 \ 6 \ B \ A \ 0 \ 7H \\ \hline C \ 5 \ E \ B \ B \ 4H \end{array}$$

- ▶ The most you can carry is 1

Substraction and borrows

- ▶ **We have to mentally reverse**
 - ▶ if $E + 6 = 14H$ then $14H - 6 = E$
- ▶ **We have to subtract column by column**
 - ▶ Start from right

$$\begin{array}{r} F \ 7 \ 6 \ C \ H \\ - \ A \ 0 \ 5 \ B \ H \\ \hline 5 \ 7 \ 1 \ 1 \ H \end{array}$$

Borrows

- ▶ **Need for borrows if a value to subtract is larger than the one we subtract from.**

- ▶ $9 - A = ???$

$$\begin{array}{r} 9 \ 2 \ H \\ - \ 4 \ F \ H \\ \hline ? \ ? \end{array}$$

- ▶ We need to add 10H (i.e. 16_{10} to the number for the subtraction to be possible.

$$\begin{array}{r} 9 \ 2 \ H \\ - \ 4_1 \ F \ H \\ \hline 4 \ 3 \ H \end{array}$$

Borrows across Multiple Columns

- ▶ We may have to transfer the borrow across more than one column

$$\begin{array}{r} F \ 0 \ 0 \ 0 \ H \\ - \ 3 \ B \ 6 \ C \ H \\ \hline ? \ ? \ ? \ ? \ H \end{array}$$

$$\begin{array}{r} F \ 0 \ 0 \ 0 \ H \\ - \ 3 \ B \ 6_1 \ C \ H \\ \hline ? \ ? \ ? \ 4 \ H \end{array}$$

$$\begin{array}{r} F \ 0 \ 0 \ 0 \ H \\ - \ 3 \ B_1 \ 6_1 \ C \ H \\ \hline ? \ ? \ 9 \ 4 \ H \end{array}$$

Borrows across Multiple Columns

$$\begin{array}{r} F \ 0 \ 0 \ 0 \ H \\ - \ 3_1 \ B_1 \ 6_1 \ C \ H \\ \hline ? \ 4 \ 9 \ 4 \ H \end{array}$$

$$\begin{array}{r} F \ 0 \ 0 \ 0 \ H \\ - \ 3_1 \ B_1 \ 6_1 \ C \ H \\ \hline B \ 4 \ 9 \ 4 \ H \end{array}$$

Binary

Binary

- ▶ There are only two digits (0 and 1) in the base
- ▶ Each column has a value two times the column to its right
- ▶ Counting

0
1
10
11
100
101
110
111
1000
1001
1010

Powers of 2

Binary	Power of 2	decimal
1	2^0	1
10	2^1	2
100	2^2	4
1000	2^3	8
10000	2^4	16
100000	2^5	32
1000000	2^6	64
10000000	2^7	128
100000000	2^8	256
1000000000	2^9	512
10000000000	2^{10}	1024
100000000000	2^{11}	2048
1000000000000	2^{12}	4096
10000000000000	2^{13}	8192
100000000000000	2^{14}	16384

Why are computer binary?

- ▶ **Other machines have been tested with base 3**
 - ▶ 1840 Thomas Fowler built a ternary calculating machine from wood
 - ▶ 1958 Nikolay Brusentsov (USSR) built the *Setun* computer
 - ▶ in 1973 he built an enhanced version called *Setun-70*
 - ▶ In the USA, a computer was built in 1973 *Ternac*
- ▶ **Because lights are either on or off**
 - ▶ In an electrical device : voltage is present or not
 - ▶ It means 1 or 0

Notation

- ▶ **Values in binary should be noted with a B**
110B means 6
whereas
110H means 272
and 110 means 110
- ▶ **Notations in scientific books use subscript**
110₂ means 6₁₀
whereas
110₁₆ means 272₁₀
and 110₁₀ means 110₁₀
- ▶ **But it is not usable inside source files or simple text editors.**

Hex as shorthand for binary

Hex as shorthand for binary

- ▶ **218 is expressed in binary:** 11011010B
- ▶ **expressed in hex:** DAH
 - ▶ AH (or 0AH in assembler) represents the number 10
 - ▶ Conversion in Binary: 1010B
 - ▶ They are the last four digits of 218 in binary
 - ▶ DH is also 1101B

218	decimal
1101 1010	binary
D A	hex

Hex as shorthand for binary

- ▶ **If we have a 32 binary number**
11110000000000001111101001101110B
- ▶ We can split it into group of 4
11110000000000001111101001101110
- ▶ Each group of 4 is represented by one Hex value

1111	0000	0000	0000	1111	1010	0110	1110
F	0	0	0	F	A	6	E

- ▶ **The hex equivalent is F000FA6EH**

Conclusion

- ▶ **Computers work only in binary**
 - ▶ Notations in Binary are too long
 - ▶ We use hex to represent binary values
- ▶ **You should be familiar with hex notation**
 - ▶ It is the center of assembler
 - ▶ One solution: do the exercises!

Source

- ▶ **Book: Assembly Language Step by Step (3rd edition)**
by Jeff Duntemann